MICROCOPY RESOLUTION TEST CHART

NATIONAL BUREAU OF STANDARDS-1963-A

(18) AR0 12958.7-M

(19)

(3)

(6) EMMY/UNIBUS INTERFACE.

Preliminary Specification.

(14) DSL-TN-88

by

(10) Walter A./Wallach

(9) Technical Note No. 88

(11) June 76

(12) 18p

DDC
RECEIVED
MAR 24 1978
B

Digital Systems Laboratory

Stanford Electronics Laboratories

Stanford University

Stanford, California

408 071

Digital Systems Laboratory

Stanford Electronics Laboratories

Technical Note No. 88

June 1976

EMMY/UNIBUS* INTERFACE
Preliminary Specification

by Walter A. Wallach

Abstract

An interface unit to allow communication between the EMMY
System bus and a DEC PDP-11 Unibus* is described. The interface
consists of three functionally independent elements- an EMMY
master/Unibus slave unit, a Unibus master/EMMY slave unit, and a
memory management unit.

The EMMY master unit allows the EMMY system to act as bus
master. On the Unibus. The 32 bit EMMY bus address is truncated
for use on the Unibus. The Unibus master unit allows the Unibus
to act as master on the EMMY bus. The 18 bit Unibus address is
mapped into the 24 bit EMMY address space through the use of one
of two techniques. The first utilizes a Page Table consisting of
four Page Setup Registers. A CAM is used to associate 2k (16 bit)
halfword pages of Unibus address space with 1k (32 bit) word pages
of EMMY addess space. The memory management element makes the
Page Setup Registers accessible to both system buses as device
registers on the Unibus. The second uses a fixed page address and
demultiplexor to recognize addresses for translation.

The memory management facility provides mapping of pages in
the Unibus address space other than the base page and the upper
two pages (which are reserved for use as device registers by
Unibus convention). Logical pages may be removed from the Unibus
by associating them with the base page or device register area.

The reader is assumed familiar with the EMMY system [1,2],
and the DEC PDP-11 Unibus [3].

* - DEC, PDP, and Unibus are the registered trademarks of Digital
Equiptment Corporation, Maynard, Massachusetts.

1.0 Introduction

The EMMY/Unibus interface provides a means of communication
between the 32-bit EMMY bus system and the 18 bit DEC Unibus r
System. Facilities are provided whereby either system may act as
master on the other bus and both systems have interrupt
capability. The entire address space of each system is available
to the other system.

Status of each system is available to the other system
through the interface. The EMMY may interrogate any CPU or device
register on the Unibus directly through the interface. The DEC
PDP-11 provides all status information directly on the bus. The
PDP-11 may access EMMY status by reading the microstatus register
(file register 0) via the memory management facility, or by
reading a status register on the Unibus, which returns the EMMY
status information available on the direct status lines (such as
Run/Halt, Power, Timeout, etc). Bus conditions such as timeout
may or may not be passed between systems, under program control.

2.0 EMMY Master Element

A device on the EMMY bus may communicate with the Unibus
through the EMMY Master Element. The EMMY device will issue a 32
bit address as described below:

EMMY ADDRESS	31		27 26 25 24	23					18	17		0

```
EMMY     31        27 26 25 24 23              18 17            0
ADDRESS ┌─────────────────────┬─────────────────┬──────────────┐
        │x x x x x  I  B  R │ 1  1  1  1  1  0 │ uuu .... uu │
        └─────────────────────┴─────────────────┴──────────────┘
```

    I - indicates an interrupt is to be isued to the PDP-11
        a halfword write must be indicated by B and R
        the data indicates the interrupt vector

    B - 1 = byte operation for write - ignored for read
        this bit corresponds to the C0 control line of the Unibus

    R - 1 = write, 0 = read
        this bit corresponds to the C1 control line of the Unibus

    uuu ... uu the low 18 bits are used as an 18 bit Unibus address

    The data portion of the EMMY bus transaction specifies 16
bits of data right justified and zero filled. Two operations must
be performed to transfer a 32 bit value.

2.1 EMMY Master Element

2.1.1 Bus Structure

    The structures of the two busses differ in certain strategic
areas. The Unibus provides seperate data, address, control, and
protocol lines. Address space is 18 bits, data words 16 bits.
Once a Master has obtained control of the bus, it may hold it as
long as it wants. The EMMY bus, on the other hand, multiplexes
data and address over the same 32 lines. Protocol is provided to
signal presence of data, address, or interrupt vector information.

2.1.2 EMMY Master Transaction

    A master on the EMMY bus requests service of the interface by
specifying an address with a unit address of F8 (hex). The low 18
bits of the EMMY address (low 2 bits of unit address plus device
address) are used as the 18 bit Unibus address. The interface
attempts to gain control of the Unibus. If the Unibus is busy
(BBSY asserted), REJECT is issued to the EMMY master. Even though
the interface may obtain control of the Unibus before the current
transaction is complete, the EMMY bus may timeout before the

                            2

requested transaction can start.

The EMMY side of the interface must monitor BBSY, NPR, and the BR lines, to determine the status of the Unibus. Care must be taken in designing the EMMY side the prevent race conditions, where the EMMY side fails to obtain the Unibus even though it has sent AACK to the requesting device. It would be best to wait for NPG before returning AACK.

Once the Unibus has been obtained (through the use of a DEC M7821 Interrupt Control Module and M796 Bus Master Control Module), the Unibus address and control portions of the EMMY address are latched and AACK asserted. This frees the EMMY Bus to transfer data. For write operations, the low 16 bits of the EMMY bus are gated to the 16 Unibus data lines when DSIG is recieved, and START signalled to the M796. When END CYCLE is signalled by the M796, DACK is asserted and the write is complete. If the Unibus protocol causes timing problems for the EMMY bus address and data can be latched and the EMMY bus released before the bus transaction is completed.

For read operations, the Unibus address and control are passed to the Unibus and START signalled to the M796. When SSYN is recieved, indicating the Unibus slave has completed its transaction, DATA WAIT will go low, strobing data onto the EMMY bus and asserting DSIG. When DACK is recieved, DATA ACCEPTED is asserted, releasng the Unibus. Data can also be be latched and the Unibus released as soon as data becomes available.

If the Unibus times out during an interface transaction, this condition will be passed to the EMMY system as an interrupt. The interrupt vector will be chosen later.

2.2 Interrupts of the PDP-11 System

An interrupt of the PDP-11 System is specified by addressing any location with the interface unit address and setting bit 26 of the EMMY address. The interface obtains control of the Unibus via the M7821 Interrupt Control Module by asserting INTR and INTR ENB lines. This makes a bus request on the BR level. When the bus has been obtained, MASTER is asserted by the M7821. The interface then asserts AACK to the EMMY bus and waits for DSIG. The low 16 bits of data are placed on the Unibus data lines and INTR START asserted to the VECTOR ADDRESS portion of the M7821. INTR DONE will be recieved when the transaction is completed. DACK may then be asserted and both buses released. Again, data may be latched and the EMMY bus released before INTR DONE is recieved.

3

3.0 Memory Management Facility

The EMMY Slave Element provides the Unibus with a means of addressing the EMMY system. Since the Unibus provides only 16 bits of processor address space, a Page Table is provided to translate Unibus references to EMMY references.

The 32K halfword address space of the Unibus is partitioned into 3 regions. The upper 4K is reserved by DEC convention for device and processor registers. The lower 8K is occupied by core memory supplied with the PDP-11/10 processor. The 20K region in between is available for mapping into the EMMY address space.

Two schemes have been developed for translating 16-bit Unibus addresses into 32 bit EMMY bus addresses. One utilizes a content-addressable memory (CAM) to associate one of 4 2K halfword Unibus pages with a 1K word EMMY page. Ten such Unibus pages are available. The other partitions the available Unibus address space into 5 fixed 4K halfword pages.

3.1 CAM-Based Memory Management Facility

The CAM-based system maps 4 pages of 2K (16 bit) halfwords of Unibus address space into 4 pages of 1K (32 bit) words of EMMY address space. Both Unibus and EMMY page addresses may be specified under program control from either system. A CAM is used to associate Unibus page addresses with EMMY pages.

p p p p	l l l l l l l l l l l l

15   12   11   0

Unibus Address

    p p p p   indicates a 2K halfword Unibus page

    l l ... l l indicates line in page

Pages 1110 and 1111 and the base page are not recognized for translation, since the base page is always present and the upper 4K halfwords are reserved by Unibus convention for device

4

registers.

```
| u u u u u u u u | p p p p | l l ... l l |
 23              16 15     12 11          0
```

u ... u   unit address

p .. p device page address

l ... l line in page

Translated EMMY Bus Address

3.1.1 Page Setup Registers - Page Table

A Page Table of 4 16-bit setup registers is provided, addressable as Unibus device registers. The low 12 bits specify a 12 bit EMMY page address, ie a unit address and 4 bit device page address. The high 4 bits specify the Unibus page address to be associated with this EMMY page. Each Unibus page consists of 2K 16-bit halfwords. The low 12 bits of the Unibus address are used to complete the EMMY address by concatenation.

These Page Registers are independent of the rest of the interface and may be addressed from the EMMY side through the interface.

A Page Setup Register is loaded by writing a 16 bit halfword to the proper Unibus address. The page table will occupy four contiguous words in the user device register area. The high 4 bits are placed in a 4-bit CAM and low 12 bits placed in the proper EMMY-address setup register.

3.1.2 EMMY Address Completion

The translation process proceeds as follows:

when a Unibus address is displayed such that Unibus A(15:12) match
a Unibus page address specified in the Page Table, the Unibus
address is recognized. (Addresses within the base page or the
upper 4K halfwords are not recognized for translation. A port may
be logically removed from the system by setting its Unibus page
address to the base page or one of the upper 2 pages). The 12
bits of the associated EMMY page address are concatenated on the
low side with the low 12 bits of the Unibus address to form an
effective EMMY address.

If an already existant page is associated with an EMMY
address, two devices will respond and results are unpredictable.

The 32 bit EMMY bus address is completed by concatenating an
8 bit control field on the high side. The control field normally
indicates right justified data and odd parity. Bit 24
(read/write) is gated directly from Unibus C1.

3.2 Fixed-Page Memory Management Facility

The fixed page scheme uses Unibus A(15:13) to drive the
translation hardware. A demultiplexor determines if the
referenced page is within the available address space (pages other
than the low 8K and high 4K halfwords). Pages 2 through 5 cause
one of 4 16 bit setup registers to be read out.

The high 5 bits contain flags which control the translation
process. These include inhibit and control byte completion
information. If the setup register indicated translation is to
proceed, the low 11 bits are concatenated on the low side with the
low 13 bits of the Unibus address, forming a 24 bit EMMY address.
The 8 bit control field is completed either by default for
halfword/byte transfer (as specified by Unibus C(1:0)), or by
setup register (for maintainance purposes). The interface does
not respond to pages where the inhibit bit is set.

6

```
┌─────────────────────────────┐
│ x  x  x  I  C  p   p ... p  p │
└─────────────────────────────┘
15           12 11 10          0
```

        Setup   Register
Flags

        x x x - unspecified
              I-Inhibit   0=translate this page reference
                          1=inhibit response to this page

                    C-Control Byte
                          0=generate MMC byte by default
                          1=MMC byte specified by setup register

                          pp...pp- high 11 bits of 24 bit EMMY
                                      address

3.3 Halfword Ports

     Three of the Page Setup Registers specify halfword/byte ports
into the EMMY system. These ports use common logic to transfer 16
bit halfwords and 8 bit bytes between the two systems under Unibus
control. Address specification reflects 2 byte or 1 byte transfer
for write (C0 gated directly from Unibus) and 2 byte transfer
always indicated for read. When byte data is to be written to the
EMMY system (Bus C(1:0) = 11), the appropriate byte is gated to
the low side (bits 7:0) of the EMMY bus (data is right justified).
These ports are intended to communicate with the EMMY main storage
system.

     MMC Byte   Read   Write
(halfword port) 1 0 1 1 0 0 0 0   1 b 1 1 0 0 0 1
                                          b - indicated by
                                              Unibus C0 -
                                              1=byte transfer

3.3.1 Halfword Transaction

     When a location associated with the halfword port is accessed
by a Unibus master, the interface responds and completes the EMMY
system address.   The EMMY bus is obtained and the address

                              7

displayed along with ASIG when MSYN is recieved.

If the operation is a halfword write, after MSYN is recieved, data is latched and SSYN returned to the Unibus. Data is placed on the low 16 bits of the EMMY bus and DSIG asserted. When DACK is recieved, the transaction is completed.

If the operation is a read, when DSIG is recieved the low 16 bits of the EMMY bus are latched and gated to the Unibus data lines. DACK and SSYN are asserted to their respective buses. This completes the slave's responsibility in the transfer. The EMMY bus is freed.

3.4 Word Port

One Page Setup Register specifies a word port into the EMMY bus system. Halfwords from the Unibus are buffered to 32 bits before transfer to or from the EMMY system. This is intended primarily as a means to access the EMMY Control Store and Register file, but may address any location on the EMMY bus.

3.4.1 Read Request

Address recognition preceeds as for the halfword ports. When a read request is made to an even halfword associated with the word port, 32 bits are read out of the translated EMMY bus location. The low 16 bits are placed on the Unibus data lines and the high 16 bits latched. When a read request for an odd halfword associated with the word port is made, the contents of the latch are placed on the Unibus data lines. The read of the EMMY system is made by shifting the translated EMMY address right by 2 bits to form a word address and concatenating an MMC byte of zeros (read 4 bytes on a word address).

To properly read a word of EMMY storage, an even/odd halfword pair must be read in ascending order by the Unibus device.

3.4.2 Write Request

When a write request is made to an even halfword associated with the word port, the data on the Unibus data lines is latched. When a write request for an odd halfword is recognized, the translated EMMY address is shifted right 2 bits, an MMC byte of 00000001 concatenated on the left to complete the FMMY address. Data on the Unibus data lines is concatenated on the left with latched data and used as the 32 bit EMMY data value. To properly

8

write a word of EMMY storage, an even/odd halfword pair must be written in ascending order.

3.5 Bus Status

A Unibus register location is provided which returns status information for the EMMY system. A read of this register returns the EMMY direct sense lines. A write of this register sets the EMMY direct control lines.

The EMMY can access any status information on the Unibus directly.

| R | I | PE | TO | P | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | PR | MC | H |

R - run/halt indicator 1=halted
    I - EMMY interrupts enabled (=1)
        PE - parity error
            TO - EMMY bus timeout
                P - EMMY powered up (=1)

                                                    PR - parity reset
                                                    MC -master clear
                                                    H -halt

        Status   Control
                        EMMY Status Register

3.6 Interrupts of the EMMY

The Unibus may interrupt the EMMY CPU by writing an interrupt vector to an Interrupt register. When this register is addressed, the interface obtains control of the EMMY bus and gates the data lines to the low 16 bits of the EMMY bus and asserts ISIG.

4.0 Implementation Notes

DEC provides modules which handle the Unibus protocols in obtaining Master status and controlling DMA transfers. (M796 and M7821). The M7821 provides bus mastership for both DMA (through NPR) and Interrupt (through BR). The protocols for slave devices are straightforeward and an M105 Address Selector will be used to access the Page Table and Registers. A modified M105 may be used to respond to virtual Unibus addresses. Bus buffering will be accomplished through an M785 Transciever Module.

An EMMY bus arbiter has been developed and will be used on the EMMY side. The interface must have high priority on the EMMY

9

bus, since all disk transfers will use the interface.

A trivial Unibus arbiter will be included in the interface unit. Initially, the only devices competing for control on the Unibus will be the disk controller and the interface. When the disk requests use of the interface, it will have priority over the EMMY (the EMMY will already be aware that the disk is busy, since it is the only device which will initiate disk operations). The arbiter will function by returning request signals on grant lines. This will allow the disk and interface to be used prior to delivery of the PDP-11 CPU.

5.0 Acknowlegement

References

1. Neuhauser, Charles, An Emulation Oriented, Dynamic Microprogrammable Processor (Version 3), TN 65, October 1975, Digital Systems Lab, Stanford University, Stanford, California 94305.

2. Neuhauser, Charles, EMMY System Peripherals, TN 77, December 1975, Digital Systems Lab, Stanford University, Stanford, California 94305.

3. Digital Equiptment Corporation, PDP11 Peripherals Handbook, Digital Equiptment Corporation, Maynard, Massachusetts 01754.

Figure 1 CAM-Based Memory Management Facility

Figure 2 Fixed-Page Memory Management Facility

12

Figure 3 Word Read Data Flow

13

Figure 4 Word Write Data Flow

14

REPORT DOCUMENTATION PAGE	READ INSTRUCTIONS BEFORE COMPLETING FORM

1. REPORT NUMBER	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
Technical Note No. 88 12958.7-M		

4. TITLE (and Subtitle)	5. TYPE OF REPORT & PERIOD COVERED
EMMY/UNIBUS INTERFACE, Preliminary Specification	Technical Note
	6. PERFORMING ORG. REPORT NUMBER

7. AUTHOR(s)	8. CONTRACT OR GRANT NUMBER(s)
Walter A. Wallach	DAAG-29-76-G-0001

9. PERFORMING ORGANIZATION NAME AND ADDRESS	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
Digital Systems Laboratory Stanford Electronics Laboratories Stanford University, Stanford, CA 943-5	

11. CONTROLLING OFFICE NAME AND ADDRESS	12. REPORT DATE
U.S. Army Research Office-Durham	June 1976
	13. NUMBER OF PAGES
	15

14. MONITORING AGENCY NAME & ADDRESS(if different from Controlling Office)	15. SECURITY CLASS. (of this report)
	15a. DECLASSIFICATION/DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT (of this Report)

Approved for public release; distribution unlimited.

17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, If different from Report)

18. SUPPLEMENTARY NOTES

The findings in this report are not to be construed as an official Department of the Army position, unless so designated by other authorized documents.

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

An interface unit to allow communication between the EMMY System bus and a DEC PDP-11 Unibus is described. The interface consists of three functionally independent elements--an EMMY master/Unibus slave unit, a Unibus master/EMMY slave unit, and a memory management unit.

The EMMY master unit allows the EMMY system to act as bus master on the Unibus. The 32 bit EMMY bus address is truncated for use on the Unibus. The Unibus master unit allows the Unibus to act as master on the EMMY bus. The 18 bit Unibus address is mapped into the 24 bit EMMY address space through the use

DD FORM 1473 EDITION OF 1 NOV 65 IS OBSOLETE
1 JAN 73

of one of two techniques. The first utilizes a Page Table consisting of four
Page Setup Registers. A CAM is used to associate 2k (16 bit) halfword pages
of Unibus address space with 1k (32 bit) word pages of EMMY address space. The
memory management element makes the Page Setup Registers accessible to both
system buses as device registers on the Unibus. The second uses a fixed page
address and demultiplexor to recognize addresses for translation.

The memory management facility provides mapping of pages in the Unibus address
space other than the base page and the upper two pages (which are reserved for
use as device registers by Unibus convention). Logical pages may be removed
from the Unibus by associating them with the base page or device register area.

The reader is assumed familiar with the EMMY system and the DEC PDP-11
Unibus.